

Amendments to the Claims:

Re-write the claims as set forth below. This listing of claims will replace all prior versions and listings, of claims in the application:

Listing of Claims:

1. (Previously presented) A signal phase shifting circuit operative to shift the phase of a STROBE signal based on a clock signal comprising:
 - a clock signal period dividing circuit having:
 - a first input that receives the clock signal,
 - a second input that receives a feedback control signal,
 - a phase shift generating circuit operatively responsive to the clock signal and the feedback control signal;
 - an output that provides a voltage controlled delay control signal for a variable delay circuit, and
 - a feedback delay matching array operatively coupled to an output of the phase shift generating circuit, that produces the feedback control signal;
 - and
 - the variable delay circuit including an input that receives the STROBE signal and being operatively responsive to the delay control signal, to provide a phase shifted output signal of the STROBE signal associated with a double data rate communication.
2. (Original) The signal phase shifting circuit of claim 1 wherein the variable delay circuit includes a delay stage and at least one phase shifted output signal drive buffer operatively coupled to the delay stage.
3. (Original) The signal phase shifting circuit of claim 2 wherein the feedback delay matching array includes a plurality of serially coupled buffer stages operatively coupled to compensate for delay variations associated with the at least one phase shifted output signal drive buffer.
4. (Previously presented) The signal phase shifting circuit of claim 1 wherein the variable delay circuit includes a delay stage and at least one multiplexer operatively coupled to vary a delay setting of the variable delay stage, and at least one phase

shifted output signal drive buffer operatively coupled to an output of the at least one multiplexer.

5. (Previously presented) The signal phase shifting circuit of claim 4 wherein the feedback delay matching array includes a plurality of serially coupled multiplexer and buffer stages operatively coupled to compensate for delay variations associated with the at least one multiplexer and the at least one phase shifted output signal drive buffer in the variable delay circuit.
6. (Previously presented) The signal phase shifting circuit of claim 1 including a data latch having a first input operatively coupled to receive data, and a second input operatively coupled to receive the phase shifted output signal of the STROBE signal.
7. (Canceled)
8. (Previously presented) The signal phase shifting circuit of claim 1 wherein the phase shift generating circuit includes a plurality of serially coupled buffers that form a controlled delay stage and wherein the feedback delay matching array includes a plurality of serially coupled multiplexer and buffer stages operatively coupled to the plurality of serially coupled buffers.
9. (Previously presented) A signal phase shifting circuit operative to shift the phase of a STROBE signal based on a clock signal comprising:
 - a reference signal period dividing circuit having:
 - a first input that receives the clock signal,
 - a second input that receives a feedback control signal,
 - a phase shift generating circuit that includes a delay lock loop circuit operatively responsive to the reference signal and the feedback control signal wherein the delay lock loop circuit includes:
 - a phase/frequency detection circuit that compares the reference signal and the feedback control signal,
 - a charge pump circuit operatively coupled to the phase/frequency detection circuit, and

a loop filter operatively responsive to an output from the charge pump circuit, that provides a delay control signal for a variable delay circuit, and
a feedback delay matching array operatively coupled to an output of the phase shift generating circuit, that produces the feedback control signal;
and
the variable delay circuit including an input that receives the STROBE signal and being operatively responsive to the delay control signal, to provide a phase shifted output signal of the STROBE signal.

10. (Previously presented) The signal phase shifting circuit of claim 9 wherein the variable delay circuit includes a delay stage and at least one multiplexer operatively coupled to vary a delay setting of the variable delay stage, and at least one phase shifted output signal drive buffer operatively coupled to an output of the at least one multiplexer.
11. (Previously presented) The signal phase shifting circuit of claim 10 wherein the feedback delay matching array includes a plurality of serially coupled multiplexer and buffer stages operatively coupled to compensate for delay variations associated with the at least one multiplexer and the at least one phase shifted output signal drive buffer in the variable delay circuit.
12. (Canceled)
13. (Previously presented) The signal phase shifting circuit of claim 9 wherein the phase shift generating circuit includes a plurality of serially coupled buffers that form a controlled delay stage and wherein the feedback delay matching array includes a plurality of serially coupled multiplexer and buffer stages operatively coupled to the plurality of serially coupled buffers.
14. (Previously presented) A data receiving circuit having a signal phase shifting circuit operative to shift the phase of a STROBE signal based on a clock signal comprising:
a reference signal period dividing circuit having:
a first input that receives the clock signal,

a second input that receives a feedback control signal,
a phase shift generating circuit that includes a delay lock loop circuit
operatively responsive to the reference signal and the feedback control signal
wherein the delay lock loop circuit includes:

- a phase/frequency detection circuit that compares the reference
signal and the feedback control signal,
- a charge pump circuit operatively coupled to the
phase/frequency detection circuit, and
- a loop filter operatively responsive to an output from the charge
pump circuit, that provides a control signal for a variable delay circuit,
and
- a feedback delay matching array operatively coupled to an output of
the phase shift generating circuit, that produces the feedback control signal;
the variable delay circuit being operatively responsive to the control signal
that provides a phase shifted output signal, and including an input that receives the STROBE
signal; and

a data latch having a first input operatively coupled to receive data, and a
second input operatively coupled to receive the phase shifted output signal.

15. (Previously presented) The signal phase shifting circuit of claim 14 wherein the
variable delay circuit includes a delay stage and at least one multiplexer operatively
coupled to vary a delay setting of the variable delay stage, and at least one phase
shifted output signal drive buffer operatively coupled to an output of the at least one
multiplexer.
16. (Previously presented) The signal phase shifting circuit of claim 15 wherein the
feedback delay matching array includes a plurality of serially coupled multiplexer and
buffer stages operatively coupled to compensate for delay variations associated with
the at least one multiplexer and the at least one phase shifted output signal drive
buffer in the variable delay circuit.
17. (Canceled)

18. (Previously presented) The signal phase shifting circuit of claim 14 wherein the phase shift generating circuit includes a plurality of serially coupled buffers that form a controlled delay stage and wherein the feedback delay matching array includes a plurality of serially coupled multiplexer and buffer stages operatively coupled to the plurality of serially coupled buffers.
19. (cancel) (1st occurrence of claim 19)
19. (Previously presented) The signal phase shifting circuit of claim 1 wherein the feedback delay matching array includes a number of serially coupled multiplexers and buffers such that the number of serially coupled multiplexers and buffers and a predetermined fraction of a clock period are reciprocals of one another.
20. (Previously presented) The signal phase shifting circuit of claim 9 wherein the feedback delay matching array includes a number of serially coupled multiplexers and buffers such that the number of serially coupled multiplexers and buffers and a predetermined fraction of a clock period are reciprocals of one another.